

REMOTE METER

**For NOVA SWITCH & NOVA
SUPERCHARGER Inverters**



Features

Complete Remote Control

Power ON/OFF & operation mode switching
Configurable settings for customized performance

Intelligent Alert System

Dual-color LED indicators (Green/Red)
Instant fault codes + audible alarm

Rugged Reliability

Flame-retardant ABS shell
Vibration & shock resistant

Comprehensive System Monitoring

Real-time voltage tracking (input/output)
Load percentage display

Optimized Visibility

High-definition backlit LCD
Wide viewing angle

Easy Installation

Precision flush-mount design
RJ12 plug-and-play connectivity

Specifications

Model	RS-RM02
Material	Flame-Retardant ABS
Display	HD Backlit LCD
Indicators	Dual-color LED + Fault Code + Buzzer
Control	ON/OFF, Mode, Settings
Monitoring	Voltage, Load, Battery
Connection	RJ12 Plug & Play
Mounting	Wall-Mount (Flush)
Product Size	136 × 86 × 32 mm (5.35 × 3.39 × 1.26 in)
Cut-out Size	110 × 59 mm (4.33 × 2.32 in)
Recess Depth	≥50 mm (1.97 in)
Compatibility	NOVA SWITCH & NOVA SUPERCHARGER Series